





M5
Maschio
Male Connector



Codice Code	∅ est. tubo Tube O.D.	JIC	F5 (UNF)	Ch5	H3	L8	T
M5-06-04	6	7/16"-20	7/16"-20	14	9	31	14
M5-08-05	8	1/2"-20	1/2"-20	16	9	31	14
M5-10-06	10	9/16"-18	9/16"-18	17	10	33	14
M5-10-08	10	9/16"-18	3/4"-16	22	11	34,5	14
M5-12-08	12	3/4"-16	3/4"-16	22	11	37,5	17
M5-12-10	12	3/4"-16	7/8"-14	27	12,5	40,5	17
M5-16-08	14÷16	7/8"-14	3/4"-16	24	11	41,5	19,5
M5-16-10	14÷16	7/8"-14	7/8"-14	27	12,5	43	19,5
M5-16-12	14÷16	7/8"-14	1.1/16"-12	32	15	47,5	19,5
M5-20-10	18-20	1.1/16"-12	7/8"-14	27	12,5	47,5	22
M5-20-12	18-20	1.1/16"-12	1.1/16"-12	32	15	50	22
M5-20-16	18-20	1.1/16"-12	1.5/16"-12	38	15	51	22
M5-25-16	25	1.5/16"-12	1.5/16"-12	38	15	52	23
M5-30-20	30-32	1.5/8"-12	1.5/8"-12	50	15	55	24,5
M5-38-24	38	1.7/8"-12	1.7/8"-12	55	15	60	27,5

TOL5
"T" Orientabile in Linea
Adjustable Branch Tee



Codice Code	∅ est. tubo Tube O.D.	JIC	F5 (UNF)	Ch1	Ch9	H	H3	L
TOL5-06-04	6	7/16"-20	7/16"-20	12	14	26	9	22,5
TOL5-08-05	8	1/2"-20	1/2"-20	14	16	28,5	9	24
TOL5-10-06	10	9/16"-18	9/16"-18	14	17	32	10	27
TOL5-10-08	10	9/16"-18	3/4"-16	19	22	37	11	28,5
TOL5-12-08	12	3/4"-16	3/4"-16	19	22	37	11	31,5
TOL5-12-10	12	3/4"-16	7/8"-14	22	27	43	12,5	34
TOL5-16-08	14÷16	7/8"-14	3/4"-16	22	22	39,5	11	36,5
TOL5-16-10	14÷16	7/8"-14	7/8"-14	22	27	43	12,5	36,5
TOL5-16-12	14÷16	7/8"-14	1.1/16"-12	27	32	49,5	15	39,5
TOL5-20-10	18-20	1.1/16"-12	7/8"-14	27	27	45,5	12,5	42
TOL5-20-12	18-20	1.1/16"-12	1.1/16"-12	27	32	49,5	15	42
TOL5-20-16	18-20	1.1/16"-12	1.5/16"-12	33	41	52	15	44,5
TOL5-25-16	25	1.5/16"-12	1.5/16"-12	33	41	52	15	46
TOL5-30-20	30-32	1.5/8"-12	1.5/8"-12	41	50	57	15	52
TOL5-38-24	38	1.7/8"-12	1.7/8"-12	48	55	60,5	15	59